## JCM Tapped Outlet Repair Clamps - 103, 104, 173, 174, 133, 134, 123, 153, 163, 164

Models of JCM Universal Clamp Couplings are available with tapped outlets for repair of direct tap pull outs and broken or split pipe requiring a service outlet.

## **HOW TO ORDER**

- 1. Select standard model, size and width clamp to fit pipe.
- 2. Change model number to corresponding Tapped Outlet Clamp Model Number.
- Select size and type of tapped outlet from outlet guide below. Note minimum widths and range/sizes.
- Add Outlet Tap Code to clamp number. Add-On outlet price to standard clamp list price.

## Ordering Example:

For standard clamp to fit 6" Cast Iron Pipe with 12" width, with 2" IP outlet, order:

103-0690-12 x 14IP

Standard Clamp Model	Becomes Tapped Outlet Clamp Model
101 Universal Clamp Coupling - Standard Range	103 Tapped Universal Clamp Coupling - Standard Range
102 Universal Clamp Coupling - Extended Range	104 Tapped Universal Clamp Coupling - Extended Range
131 All Stainless Steel UCC - Std Range	133 Tapped All Stainless Steel UCC - Std Range
132 All Stainless Steel UCC - Extd Range	134 Tapped All Stainless Steel UCC - Extd Range
121 Gas Repair Clamp	123 Tapped Gas Service Clamp
151 Gas Repair Clamp	153 Tapped All Stainless Steel Gas Service Clamp
161 All Stainless Steel Fabricated Lug Clamp	163 All Stainless Steel Tapped Fabricated Lug Clamp
162 All Stainless Steel Fabricated Lug Clamp - Ext Range	164 All Stainless Steel Tapped Fabricated Lug Clamp - Ext Range
171 UCC - Standard Range - Removeable Lug	173 Tapped UCC - Standard Range - Removeable Lug
172 UCC - Extended Range - Removeable Lug	174 Tapped UCC - Standard Range - Removeable Lug

				ADD OUTLET TAP CODE	
CLAMP RANGE/SIZE (IN.)	MINIMUM CLAMP LENGTH (IN.)	TYPE OF THREAD	TAP SIZE	IP ORDER TAP CODE	CC ORDER TAP CODE
2.38 - 4.80	6	IP or CC	3/4"	06	07
			1"	08	09
2.38 - 14.00	7-1/2	IP or CC	3/4"	06	07
			1"	08	09
4.50 - 14.00	12	IP or CC	1-1/4"	10	11
4.50 - 14.00	12	IP or CC	1-1/2"	12	13
4.50 - 14.00	12	IP	2"	14	-
4.50 - 14.00	12	CC	2"	-	15



JCM 133 153



JCM 163



